

Annex to declaration of accreditation (scope of accreditation)
 Normative document: EN ISO/IEC 17025:2017
 Registration number: **K 159**

of **Siemens Industry Software Netherlands B.V.**

This annex is valid from: **25-03-2026** to **01-08-2028**

Replaces annex dated: **18-07-2024**

Location(s) where activities are performed under accreditation

Head Office

Weidehek 53
 4824 AT
 Breda
 The Netherlands

Location	Abbreviation/ location code
Weidehek 53 4824 AT Breda The Netherlands	BR

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
LF 0 0	DC/LF electricity				BR
LF 1 0	Direct voltage			Generating. <i>U</i> stands for generated DC voltage	BR
	0.00 V ≤ <i>U</i> ≤ 0.25 V -0.25 V ≤ <i>U</i> ≤ 0.00 V		22 μV		
	0.25 V < <i>U</i> ≤ 4 V -4 V ≤ <i>U</i> < -0.25 V		220 μV		
	4 V < <i>U</i> ≤ 10 V -10 V ≤ <i>U</i> < -4 V		460 μV		

This annex has been approved by the Board of the Dutch Accreditation Council, on its behalf,

J.A.W.M. de Haas

¹ Calibration and Measurement Capability (CMC): Demonstrated measurement uncertainty, with coverage probability of 95%, in a given measurement point or measurement range. Measurement uncertainty, *U*, is calculated according to EA-4/02 "Evaluation of the Uncertainty of Measurement in Calibration".

of **Siemens Industry Software Netherlands B.V.**

This annex is valid from: **25-03-2026 to 01-08-2028**

Replaces annex dated: **18-07-2024**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
LF 1 0	Direct voltage			Measuring the internal reference generator with a DMM. <i>U</i> stands for generated DC voltage	BR
	0.00 V ≤ <i>U</i> ≤ 0.25 V -0.25 V ≤ <i>U</i> ≤ 0.00 V		22 μV		
	0.25 V < <i>U</i> ≤ 4 V -4 V ≤ <i>U</i> < -0.25 V		220 μV		
LF 1 0	Direct voltage			Measuring residual offset. <i>IR</i> stands for "Input Range"	BR
	0 mV ≤ <i>IR</i> ≤ 100 mV -100 mV ≤ <i>IR</i> ≤ 0 mV		0.6 μV	Bridge channels	
	100 mV < <i>IR</i> ≤ 316 mV -316 mV ≤ <i>IR</i> < -100 mV		1.2 μV	Bridge channels	
	316 mV < <i>IR</i> ≤ 1 V -1 V ≤ <i>IR</i> < -316 mV		2.2 μV	Bridge channels	
	1 V < <i>IR</i> ≤ 3.16 V -3.16 V ≤ <i>IR</i> < -1 V		8.8 μV	Bridge channels	
	3.16 V < <i>IR</i> ≤ 10 V -10 V ≤ <i>IR</i> < -3.16 V		21 μV	Bridge channels	
	0 mV ≤ <i>IR</i> ≤ 316 mV -316 mV ≤ <i>IR</i> ≤ 0 mV		4.8 μV	V/ICP channels	
	316 mV < <i>IR</i> ≤ 1 V -1 V ≤ <i>IR</i> < -316 mV		5.2 μV	V/ICP channels	
	1 V < <i>IR</i> ≤ 3.16 V -3.16 V ≤ <i>IR</i> < -1 V		8.0 μV	V/ICP channels	
	3.16 V < <i>IR</i> ≤ 10 V -10 V ≤ <i>IR</i> < -3.16 V		21 μV	V/ICP channels	
LF 3 0	Alternating voltage			Measuring amplitude accuracy. <i>IR</i> stands for "Input Range"	BR
	<i>IR</i> ≤ 100 mV	1000 Hz	48 μV	Bridge channels	
	100 mV < <i>IR</i> ≤ 316 mV	1000 Hz	66 μV	V/ICP and bridge channels	
	316 mV < <i>IR</i> ≤ 1 V	1000 Hz	120 μV	V/ICP and bridge channels	
	1 V < <i>IR</i> ≤ 3.16 V	1000 Hz	310 μV	V/ICP and bridge channels	

of **Siemens Industry Software Netherlands B.V.**

This annex is valid from: **25-03-2026 to 01-08-2028**

Replaces annex dated: **18-07-2024**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
	3.16 V < IR ≤ 10 V	1000 Hz	530 μV	V/ICP and bridge channels	
LF 3 0	Alternating charge			Measuring amplitude accuracy. Using internal capacitor for voltage to charge conversion. IR stands for "Input Range"	BR
	IR ≤ 316 pC	1000 Hz	3.0 pC	Charge input channels	
	316 pC < IR ≤ 1 nC	1000 Hz	9.2 pC	Charge input channels	
	1 nC < IR ≤ 3.16 nC	1000 Hz	30 pC	Charge input channels	
	3.16 nC < IR ≤ 10 nC	1000 Hz	96 pC	Charge input channels	
LF 3 0	Crosstalk (voltage)			Measuring interchannel crosstalk. IR stands for "Input Range"	BR
	IR ≤ 100 mV	1.5 kHz ~ 15 kHz	60 nV	Bridge channels	
	100 mV < IR ≤ 316 mV	1.5 kHz ~ 15 kHz	68 nV	V/ICP and bridge channels	
	316 mV < IR ≤ 1 V	1.5 kHz ~ 15 kHz	150 nV	V/ICP and bridge channels	
	1 V < IR ≤ 3.16 V	1.5 kHz ~ 15 kHz	0.4 μV	V/ICP and bridge channels	
	3.16 V < IR ≤ 10 V	1.5 kHz ~ 15 kHz	1.3 μV	V/ICP and bridge channels	
LF 3 0	Crosstalk (charge)			Measuring interchannel crosstalk. Using internal capacitor for voltage to charge conversion. IR stands for "Input Range"	BR
	IR ≤ 316 pC	1.5 kHz ~ 15 kHz	68 aC	Charge input channels	
	316 pC < IR ≤ 1 nC	1.5 kHz ~ 15 kHz	150 aC	Charge input channels	
	1 nC < IR ≤ 3.16 nC	1.5 kHz ~ 15 kHz	0.4 fC	Charge input channels	
	3.16 nC < IR ≤ 10 nC	1.5 kHz ~ 15 kHz	1.3 fC	Charge input channels	
LF 3 0	Distortion (voltage)			Measuring harmonics. IR stands for "Input Range"	BR
	IR ≤ 100 mV	993.75 Hz	120 nV	Bridge channels	
	100 mV < IR ≤ 316 mV	993.75 Hz	140 nV	V/ICP and bridge channels	
	316 mV < IR ≤ 1 V	993.75 Hz	290 nV	V/ICP and bridge channels	

of **Siemens Industry Software Netherlands B.V.**

This annex is valid from: **25-03-2026** to **01-08-2028**

Replaces annex dated: **18-07-2024**

HCS code	Measured quantity, Range	Frequency	CMC ¹	Remarks	Location
	$1\text{ V} < IR \leq 3.16\text{ V}$	993.75 Hz	0.8 μV	V/ICP and bridge channels	
	$3.16\text{ V} < IR \leq 10\text{ V}$	993.75 Hz	2.6 μV	V/ICP and bridge channels	
LF 3 0	Distortion (charge)			Measuring harmonics. Using internal capacitor for voltage to charge conversion. <i>IR</i> stands for "Input Range"	BR
	$IR \leq 316\text{ pC}$	993.75 Hz	140 aC	Charge input channels	
	$316\text{ pC} < IR \leq 1\text{ nC}$	993.75 Hz	290 aC	Charge input channels	
	$1\text{ nC} < IR \leq 3.16\text{ nC}$	993.75 Hz	0.8 fC	Charge input channels	
	$3.16\text{ nC} < IR \leq 10\text{ nC}$	993.75 Hz	2.6 fC	Charge input channels	
TF 0 0	Time and frequency				
TF 2 1	Frequency	800 Hz	0.1 Hz	Measuring the internal reference frequency accuracy, representing system clock accuracy	BR

Remark(s):

All entries in this scope relate to the calibration of Simcenter SCADAS signal conditioning and data acquisition equipment.